Helmholtz-Zentrum Dresden-Rossendorf (HZDR)



# Coherent coupling of metamaterial resonators with dipole transitions of boron acceptors in Si

Meng, F.; Han, F.; Kentsch, U.; Pashkin, O.; Fowley, C.; Rebohle, L.; Thomson, M. D.; Suzuki, S.; Asada, M.; Roskos, H. G.;

Originally published:

September 2022

# Optics Letters 47(2022), 4969-4972

DOI: https://doi.org/10.1364/OL.466392

Perma-Link to Publication Repository of HZDR:

https://www.hzdr.de/publications/Publ-35354

Release of the secondary publication on the basis of the German Copyright Law § 38 Section 4.

# Electromagnetic coupling of split-ring resonators with dipole transitions of boron acceptors in Si at

# 7.33 and 8.28 THz

FANQI MENG<sup>1,5</sup>, FEIFAN HAN<sup>2</sup>, ULRICH KENTSCH<sup>3</sup>, ALEXEJ

- PASHKIN<sup>3</sup>, CIARAN FOWLEY<sup>3</sup>, LARS REBOHLE<sup>3</sup>, MARK D. THOMSON<sup>1</sup>, SAFUMI SUZUKI<sup>2</sup>, MASAHIRO ASADA<sup>4</sup>, AND HARTMUT G.
- Roskos<sup>1,6</sup>

<sup>1</sup>Physikalisches Institut, Johann Wolfgang Goethe-Universität, Frankfurt am Main, Germany

<sup>2</sup>Department of Electrical and Electronic Engineering, Tokyo Institute of Technology, Tokyo, Japan

- <sup>3</sup>Institute of Ion Beam Physics and Materials Research, Helmholtz-Zentrum Dresden-Rossendorf, 01328 10
- 11 Dresden, Germany

<sup>4</sup>Institute of Innovative Research, Tokyo Institute of Technology, Tokyo, Japan 12

<sup>5</sup>fmeng@physik.uni-frankfurt.de 13

<sup>6</sup>roskos@physik.uni-frankfurt.de 14

Abstract: We investigate the coherent coupling of split-ring resonators of a metamaterial with 15 hydrogen-like boron acceptors in Si at cryogenic temperatures. When the resonance frequency 16 of the metamaterial, chosen to be in the range 7-9 THz, superimposes the transition frequency 17 from the ground state of the acceptor to an excited state, Rabi splitting is observed. The splitting 18 shows a square-root dependence on the density of the acceptors. Our experiments may help to 19 open a possible route for the investigation of quantum information processes employing strong 20 coupling of dopants in cavities. 21

#### © 2022 Optica Publishing Group 22

In the past decades, light-matter interaction in photonic cavities has provided a unique testbed 23 for the investigation of fundamental quantum physics. By coupling with the cavity photons, 24 electronic transitions of the material can be substantially modified, especially in the *strong* 25 *coupling* regime, where polariton quasi-particles are formed [1]. These new dressed states reveal 26 themselves by Rabi-split transitions in the absorption spectra, if the rate of energy exchange 27 between matter and the cavity photons is larger than the rate of energy loss of both cavity and 28 matter. Strong light-matter interaction was first studied with free atoms, and Rabi splitting 29 was reported to be at hundreds of MHz. In recent years, there is an intense interest to explore 30 the *ultra-strong coupling* regime, where the Rabi splitting reaches a substantial portion of the 31 resonance frequency of the cavity [2], and even the deep strong coupling regime where the Rabi 32 splitting is larger than the resonance frequency of the cavity [3]. A strong motivation comes 33 from quantum computing and quantum information processing, where coupling of the relevant 34 excitations in cavities plays an important role [4]. 35

Access to these regimes with free atoms is, however, hindered by the relatively weak electron 36 transition dipole moments encountered there [5]. Atoms embedded in a crystalline solid-state 37 matrix are more suitable for such investigations. This is especially true for atoms which represent 38 dilute shallow dopants. Such dopants are essential ingredients of all semiconductor devices. Their 39 energy states can be modeled in a hydrogen-like fashion. Due to the dielectric environment and 40 the orbital interaction with the host material, the transition dipole moments can be several orders 41 of magnitude larger than those of free atoms [6]. At room temperature, the atoms are ionized, 42 and the electrons, respectively holes, are free to move. At low temperature, the charge carriers 43 are frozen in their ground states. Upon irradiation with electromagnetic radiation, the charge 44 carriers can be excited to higher energy states via dipole-allowed transitions. This is one reason 45

why dopants exhibit great potential for applications in atomic-scale solid-state spintronics [7]
and quantum computing [8,9]. In addition, quantum devices based on dopants in Si can be
readily integrated into the current semiconductor technology. In this report, we demonstrate
strong interaction of transitions between boron acceptor states in Si with the fundamental-mode
plasmonic excitation of split-ring oscillators, observing a Rabi splitting as large as 0.4 THz.

The experiments were performed with boron-doped Si samples prepared by ion implantation 51 of high-resistivity Si wafers (purchased from UniversityWafer Inc., with the thickness of 500  $\mu$ m). 52 To create a homogenously doped surface layer of  $1-\mu m$  thickness, multi-energy implantation 53 was employed. Two specimens were prepared with boron densities of  $4 \times 10^{16}$  cm<sup>-3</sup> and 54  $2 \times 10^{17}$  cm<sup>-3</sup>. After implantation, rapid thermal annealing was carried out to remove defects in 55 the Si lattice generated by the implantation [10]. Fig. 1a shows the linear transmission spectrum 56 of an annealed sample with a boron density of  $2 \times 10^{17}$  cm<sup>-3</sup>, measured by Fourier transform 57 far-infrared spectroscopy at a sample temperature of 20 K (a reference transmission spectrum 58 taken at 100 K was used for background subtraction). The spectrum exhibits the expected series 59 of discrete transitions from the boron ground-state to excited states at 7.33 THz  $(1\Gamma_8^+ \rightarrow 1\Gamma_9^-)$ , 60 8.28 THz  $(1\Gamma_8^+ \rightarrow 2\Gamma_8^-)$ , 9.5 THz  $(1\Gamma_8^+ \rightarrow 1\Gamma_7^-, 1\Gamma_6^-)$ , and 10.27 THz  $(1\Gamma_8^+ \rightarrow 2\Gamma_6^-, 6\Gamma_8^-)$  [11]. The transition lines are well separated from each other even at this fairly high dopant density. 61 62 The widths of the lower two transition lines are 0.18 THz and 0.19 THz, respectively. 63



Fig. 1. (a) Measured transmission spectrum of boron-implanted Si at 20 K (boron density:  $2 \times 10^{17}$  cm<sup>-3</sup>). (b) Measured transmission spectrum of a metamaterial on boron-implanted Si at 100 K. Both figures cover an x-axis range of 5 THz. The inset shows an image taken by atomic force microscopy (AFM) of the gold pattern.

Metamaterial patterns with unit cells consisting of metallic square-shaped split-ring resonators 64 (SRR) were prepared by e-beam lithography on the surfaces of the implanted Si specimens. We 65 designed metamaterials [12] with six different fundamental resonance frequencies to cover the 66 lower two impurity transition lines. An AFM image of four unit cells of one of the fabricated 67 metamaterials is shown in the inset of Fig. 1b. All six metamaterials have the same period, 68 metal stripe width and gap width of 5.2  $\mu$ m, 0.6  $\mu$ m and 0.6  $\mu$ m, respectively. Only the 69 length of the outer edges varies, with values of 3.0, 2.9, 2.8, 2.7, 2.6 and 2.5  $\mu$ m, respectively. 70 Transmission spectra of the metamaterial-covered doped specimens, which were recorded at a 71 sample temperature of 100 K, where the dopants are ionized and the impurity transitions are 72 absent, revealed frequencies of the fundamental resonances between 7.0 THz and 9.09 THz. 73 A representative spectrum of a metamaterial with a SRR edge length of 2.7  $\mu$ m is shown in 74 Fig. 1b (the spectrum was derived by subtracting a reference transmission spectrum of an equally 75 doped Si specimen without metamaterial pattern on it). The full width at half maximum of the 76 metamaterial resonance is 1.4 THz, with a Q-factor of 6. The measured resonance frequency is 77

<sup>78</sup> 8.08 THz at 100 K, and decreases to below 8.0 THz at 20 K. Simulations with the CST Maxwell <sup>79</sup> solver, assuming the room-temperature values of the Au conductivity of  $4.5 \times 10^6$  S/m and of the <sup>80</sup> Si dielectric constant of 11.9, yield a resonance frequency of 8.3 THz [11].

Figure 2a shows transmission spectra of all six metamaterial-covered Si samples with a boron density of  $2 \times 10^{17}$  cm<sup>-3</sup> at a temperature of 20 K. The positions of the boron acceptor transitions at 7.33 THz, 8.28 THz and 9.5 THz are indicated by vertical dashed lines. The SRR resonances are well below the highest-lying of these three transitions. One finds in the spectra of Fig. 2a, that the frequency of this 9.5-THz transition is not affected by the presence of the metamaterial. In contrast, the two lower transitions (at 7.33 THz and 8.28 THz) exhibit level splitting, if the resonance frequency of the metamaterial is close to the respective acceptor transition line.



Fig. 2. (a) Transmission spectra of metamaterial-covered doped Si with a boron density of  $2 \times 10^{17}$  cm<sup>-3</sup> at 20 K. Different colors represent metamaterials of different resonance frequencies. The legend specifies the resonance frequency of the metamaterials measured at 100 K. The vertical dashed lines indicate transition frequencies of the bare dopants. (b) Frequency positions of the transmission minima as a function of the metamaterial's resonance frequency. An avoided-crossing behavior is observed around center frequencies of 7.40 THz and 8.29 THz (marked by dashed horizontal lines), slightly higher than the respective transition frequencies of 7.33 THz and 8.28 THz of the bare impurities.

Figure 2b displays the transmission minima extracted from the spectra as a function of the 88 resonance frequency of the metamaterial. The data points group in three features (branches) 89 which are characteristic for Rabi-split hybrid transitions, as one expects them to arise from the 90 electromagnetic coupling of the metamaterial resonators and the dopants [13]. The three branches 91 are plotted in different coloring: a lower branch (LB, black), a middle branch (MB, red) and an 92 upper branch (UB, blue). They exhibit anti-crossing signatures around frequencies of 7.40 THz 93 and 8.29 THz (marked by horizontal dashed lines in Fig. 2b), slightly higher than the frequencies 94 of the bare impurity transitions. The minimal frequency splitting (Rabi splitting) is 0.3 THz at 95 the lower transition line, and 0.4 THz, respectively, at the higher one. The smaller value of the 96 Rabi splitting at the lower transition line is attributed to a smaller transition dipole moment. 97

The coupling strength g of light-matter interaction is given by half the Rabi splitting of the 98 ensuing polariton branches. For the second transition, the value of g is hence 0.2 THz. This 99 value is to be compared with the linewidth  $\gamma$  of the bare impurity transition ( $\gamma = 0.19$  THz). 100 If one assume the linewidth to be of homogeneous nature, it represents the population decay 101 rate of the upper state of the impurity transition. The linewidth of the metamaterial resonance, 102 on the other hand, represents the decay rate of the resonator mode. Fig. 1b yields  $\kappa = 1.4$  THz. 103 With these values, one finds that the condition  $2g < (\gamma + \kappa)/2$  is fulfilled, which implies that 104 the coupled system is not in the strong-interaction regime. Using the classification scheme of 105

Ref. [14], the relationships  $g \approx \gamma$  and  $g < \kappa$  categorize the coupled system to be at the boundary between the weak-coupling regime and the electromagnetically induced transparency regime.



Fig. 3. (a) Temperature dependence of the transmission spectra of Si doped at a boron density of  $2 \times 10^{17}$  cm<sup>-3</sup> and covered by a metamaterial with a room-temperature SRR resonance at 8.56 THz. Different colors represent different temperatures, as specified in the legend. (b) 20-K transmission spectra of metamaterial-covered doped Si with a boron density of  $4 \times 10^{16}$  cm<sup>-3</sup>, for two SRR resonances with 100-K resonance positions as indicated in the legend.

The vertical dashed respectively dotted lines indicate the 8.28-THz transition frequency of the bare dopants.

Figure 3a shows the transmission spectra of metamaterial-covered doped Si with a boron 108 density of  $2 \times 10^{17}$  cm<sup>-3</sup> at different temperatures from 80 down to 10 K. At a temperature of 109 80 K, the spectra exhibit only the resonance of the metamaterial with a transmission minimum at 110 around 8.56 THz. As the temperature decreases, the absorption features of the boron dopants 111 emerge: The transition lines at 7.33 THz and 9.5 THz, and a double-dip feature around the 112 8.28-THz transition, indicating Rabi splitting of that transition. As the resonance frequency of 113 the metamaterial shifts to lower frequency when the temperature is decreased further and further, 114 first the high-frequency dip is more pronounced, then it is the low-frequency one. At 20 K, they 115 are almost equally strong, indicating that the resonance frequency of the metamaterial should 116 be close to 8.28 THz at this temperature. The Rabi splitting amounts to 0.4 THz, as discussed 117 previously. 118

Figure 3b displays two transmission spectra measured with samples with a dopant density 119 of  $4 \times 10^{16}$  cm<sup>-3</sup> at 20 K. Two different metamaterials are deposited onto the specimens, 120 with resonance frequencies at 8.08 and 8.56 THz (frequencies determined at 100 K). For the 121 metamaterial with a 100-K resonance at 8.08 THz, the resonance frequency of the cavity is detuned 122 from the transition lines, while the resonance curve of the other metamaterial superimposes with 123 the transition line at 8.28 THz. The transmission spectrum measured with that specimen exhibits 124 a Rabi splitting of 0.23 THz at 20 K. Comparing this value with that of the corresponding sample 125 with the higher doping density, one finds that the ratio of the Rabi splittings (0.4/0.22=1.8) is 126 similar to the square root of the doping densities ( $\sqrt{2 \times 10^{17}/4 \times 10^{16}} = 2.2$ ). This is reasonably 127 consistent with the prediction of cavity quantum electrodynamics that the coupling strength 128 should be proportional to the square root of the number of particles involved in the coupling [12]. 129 The difference between these two ratios may be attributed to the uncertainty of the doping density 130 resulting from variations of the ion beam fluences of the multi-energy ion implantation process. 131 In conclusion, we have achieved coherent interaction between electronic transitions of boron 132 acceptors in Si and metamaterial resonators. A Rabi splitting as large as 0.4 THz is observed. 133 However, due to the low Q-factor of the split-ring resonators of the metamaterial, the coupling 134

strength is still much less than the dissipation rate of the metamaterial. In order to achieve

<sup>136</sup> stronger coupling, a metamaterial with a higher Q-factor, such as toroidal metamaterial [15] or a

<sup>137</sup> Fano-type metamaterial [16], should be adopted in the future. Another potential approach is

to employ a two-dimensional photonic crystal cavity which possesses a very high Q-factor (of

about 1000 [17]), such that it may even be possible to operate in the strong coupling regime while

<sup>140</sup> keeping the dopant density low.

### 141 Acknowledgements

This research work was funded by DFG project RO 770/41-1 and RO 770/46-1. The authors
 thank Lichuan Zheng and Sebastian Kölsch for the AFM pictures of the metamaterials.

### 144 Disclosures

<sup>145</sup> The authors declare that there are no conflicts of interest related to this article.

## 146 Data Availability

Data underlying the results presented in this paper are not publicly available at this time but may
 be obtained from the authors upon reasonable request.

### 149 **References**

- S. Haroche, "Nobel lecture: controlling photons in a box and exploring the quantum to classical boundary," Rev.
   Mod. Phys. 85, 1083–1102 (2013).
- G. Scalari, C. Maissen, D. Turcinková, D. Hagenmüller, S. D. Liberato, C. Ciuti, C. Reichl, D. Schuh, W. Wegscheider,
   M. Beck, and J. Faist, "Ultrastrong coupling of the cyclotron transition of a 2D electron gas to a THz metamaterial,"
   Science 335, 1323–1326 (2012).
- A. Bayer, M. Pozimski, S. Schambeck, D. Schuh, R. Huber, D. Bougeard, and C. Lange, "Terahertz light-matter interaction beyond unity coupling strength," Nano Lett. 17, 6340–6344 (2017).
- J. M. Gambetta, J. M. Chow, and M. Steffen, "Building logical qubits in a superconducting quantum computing system," npj Quantum Inf. 3 (2017).
- D. J. Alton, N. P. Stern, T. Aoki, H. Lee, E. Ostby, K. J. Vahala, and H. J. Kimble, "Strong interactions of single atoms and photons near a dielectric boundary," Nat. Phys. 7, 159–165 (2010).
- M. A. W. van Loon, N. Stavrias, N. H. Le, K. L. Litvinenko, P. T. Greenland, C. R. Pidgeon, K. Saeedi, B. Redlich,
   G. Aeppli, and B. N. Murdin, "Giant multiphoton absorption for THz resonances in silicon hydrogenic donors," Nat.
   Photonics 12, 179–184 (2018).
- 164 7. M. J. Gullans and J. M. Taylor, "Optical control of donor spin qubits in silicon," Phys. Rev. B 92 (2015).
- P. T. Greenland, S. A. Lynch, A. F. G. van der Meer, B. N. Murdin, C. R. Pidgeon, B. Redlich, N. Q. Vinh, and
   G. Aeppli, "Coherent control of Rydberg states in silicon," Nature 465, 1057–1062 (2010).
- 9. B. E. Kane, "A silicon-based nuclear spin quantum computer," Nature **393**, 133–137 (1998).
- 10. J. Narayan and O. W. Holland, "Rapid thermal annealing of ion-implanted semiconductors," J. Appl. Phys. 56, 2913–2921 (1984).
- 11. F. Meng, M. D. Thomson, Q. ul Islam, B. Klug, A. Pashkin, H. Schneider, and H. G. Roskos, "Intracavity third-harmonic generation in Si:B pumped by intense terahertz pulses," Phys. Rev. B 102, 075205 (2020).
- 172 12. F. Meng, M. D. Thomson, B. Klug, D. Čibiraitė, Q. ul Islam, and H. G. Roskos, "Nonlocal collective ultrastrong interaction of plasmonic metamaterials and photons in a terahertz photonic crystal cavity," Opt. Express 27, 24455–24468 (2019).
- 13. F. Meng, M. D. Thomson, B. Klug, and H. G. Roskos, "Strong interaction between two photons and a plasmon of a complementary metamaterial in a terahertz dual cavity," Opt. Express 29, 42420 (2021).
- 14. X. Zhang, C. L. Zou, L. Jiang, and H. X. Tang, "Strongly coupled magnons and cavity microwave photons," Phys.
   Rev. Lett. 113, 156401 (2014).
- 179 15. T. Kaelberer, V. A. Fedotov, N. Papasimakis, D. P. Tsai, and N. I. Zheludev, "Toroidal dipolar response in a
   metamaterial," Science 330, 1510–1512 (2010).
- 16. V. A. Fedotov, M. Rose, S. L. Prosvirnin, N. Papasimakis, and N. I. Zheludev, "Sharp trapped-mode resonances in planar metamaterials with a broken structural symmetry," Phys. Rev. Lett. 99 (2007).
- 17. C. M. Yee and M. S. Sherwin, "High-Q terahertz microcavities in silicon photonic crystal slabs," Appl. Phys. Lett.
   94, 154104 (2009).